



10.1.13 Editors - Compositor Editor - Header - Add Menu - Transform

Table of content

Detailed table of content.....	1
Add menu - Transform.....	3
Rotate.....	4
Scale.....	4
Transform.....	5
Translate.....	6
Corner Pin.....	7
Crop.....	8
Displace.....	8
Flip.....	9
Map UV.....	9
Lens Distortion.....	10
Movie Distortion.....	11

Detailed table of content

Detailed table of content


Detailed table of content.....	1
Add menu - Transform.....	3
Rotate.....	4
Inputs.....	4
Image.....	4
Degr.....	4
Properties.....	4
Filter.....	4
Nearest.....	4
Bilinear.....	4
Bicubic.....	4
Outputs.....	4
Image.....	4
Scale.....	4
Inputs.....	4
Image.....	4
X, Y.....	5
Properties.....	5
Space.....	5
Relative.....	5
Absolute.....	5
Scene Size.....	5
Render Size.....	5
Stretch, Fit, Crop.....	5
X, Y.....	5
Outputs.....	5
Image.....	5

Transform.....	5
Inputs.....	5
Image.....	5
X, Y.....	6
Angle.....	6
Scale.....	6
Properties.....	6
Filter.....	6
Nearest.....	6
Bilinear.....	6
Bicubic.....	6
Outputs.....	6
Image.....	6
Translate.....	6
Inputs.....	6
Image.....	6
X, Y.....	6
Properties.....	7
Relative.....	7
Wrapping.....	7
Outputs.....	7
Image.....	7
Corner Pin.....	7
Inputs.....	7
Image.....	7
Corners.....	7
Outputs.....	7
Image.....	7
Plane.....	7
Crop.....	8
Inputs.....	8
Image.....	8
Properties.....	8
Crop Image Size.....	8
Relative.....	8
Crop Region Values.....	8
Outputs.....	8
Image.....	8
Displace.....	8
Inputs.....	8
Image.....	8
Vector.....	8
Scale X, Y.....	9
Outputs.....	9
Image.....	9
Flip.....	9
Inputs.....	9
Image.....	9
Properties.....	9
Axis.....	9
Outputs.....	9
Image.....	9
Map UV.....	9

Inputs.....	9
Image.....	9
UV.....	10
Properties.....	10
Alpha.....	10
Outputs.....	10
Image.....	10
Lens Distortion.....	10
Inputs.....	10
Image.....	10
Distortion.....	10
Dispersion.....	10
Properties.....	10
Projector.....	10
Jitter.....	10
Fit.....	11
Outputs.....	11
Image.....	11
Movie Distortion.....	11
Distortion vs Undistortion.....	11
Calculating Distortion.....	11
Inputs.....	11
Image.....	11
Properties.....	12
Movie Clip.....	12
Distortion Method.....	12
Undistort.....	12
Distort.....	12
Outputs.....	12
Image.....	12


Add menu - Transform

These nodes distort the image in some fashion. They work either on the whole image, or by using a mask to vary the effect over the image.



Rotate

This node rotates an image.



Inputs

Image

Standard image input.


Degr

Rotation angle in degree. Positive values rotate clockwise and negative ones counterclockwise.

Properties

Filter

Interpolation Methods.



Nearest

No interpolation. This method uses the nearest neighboring pixel.

Bilinear

Simple interpolation between adjacent pixels.

Bicubic

Highest quality interpolation.


Outputs

Image

Standard image output.

Scale

The Scale node scales the size of an image.



Inputs

Image

Standard image input.


X, Y

Scale in the axis directions, only available if Space is set to Relative or Absolute.

Properties

Space

Coordinate Space to scale relative to.



Relative

Percentage values relative to the dimensions of the image input.

Absolute


Size of an image by using absolute pixel values.

Scene Size

Sizes an image to the size of the final render resolution for the scene. For example, rendering a scene at the standard 1080p resolution but setting the render percentage at 50%, will produce a 1080p image with the scene scaled down 50% and leaving the rest of the image as alpha.

Render Size

Image dimensions set in the Render panel.



Stretch, Fit, Crop

Render Size setting. Stretch distorts the image so that it fits into the render size. Fit scales the image until the bigger axis “fits” into the render size. Crop cuts the image so that it is the same aspect ratio as the render size.

X, Y

Render Size setting. Offset factor for the final scaled image.

Outputs

Image

Standard image output.


Transform

The Transform node combines the functionality of three other nodes: Scale, translate, and rotate nodes.

Inputs

Image

Standard image input.



X, Y

Used to move the input image horizontally and vertically.

Angle

Used to rotate an image around its center. Positive values rotate counter-clockwise and negative ones clockwise.


Scale

Used to resize the image. The scaling is relative, meaning a value of 0.5 gives half the size and a value of 2.0 gives twice the size of the original image.

Properties

Filter

Interpolation Methods.



Nearest

No interpolation, uses nearest neighboring pixel.

Bilinear

Simple interpolation between adjacent pixels.

Bicubic

Highest quality interpolation.

Outputs

Image

Standard image output.

Translate

The Translate node moves an image.

Could also be used to add a 2D camera shake.


Inputs

Image

Standard image input.

X, Y

Used to move the input image horizontally and vertically.



Properties

Relative

Percentage translation values relative to the input image size.

Wrapping

Repeat pixels on the other side when they extend over the image dimensions.

None, X Axis, Y Axis, Both Axis



Outputs

Image

Standard image output.

Corner Pin

The Corner Pin node uses explicit corner values for a plane warp transformation. It works like the Plane Track Deform node, but without using “plane track” data from the Movie Clip Editor.

Inputs

Image

Standard image input.

Corners

Four vector inputs to define the plane warping. (Z component of vector inputs is ignored.)


Outputs

Image

Standard image output. (The image after distorting.)

Plane

A black-and-white alpha mask of the plane.




Crop

The Crop Node takes an input image and crops it to a selected region.

Inputs

Image

Standard image input.



Properties

Crop Image Size

When enabled, the image size is cropped to the specified region. When disabled, the image remains the same size, and uncropped areas become transparent pixels.

Relative

When enabled, crop dimensions are a percentage of the image's width and height. When disabled, the range of the Crop Region Values are the width and height of the image in pixels.

Crop Region Values

Define borders of the crop region. Lower, upper, left, right.

Outputs

Image

Standard image output.

Displace


The Displace Node displaces the pixel position based on an input vector.

This node could be used to model phenomena, like hot air distortion, refraction's of uneven glass or for surreal video effects.

Inputs

Image

Standard image input.



Vector

Input of the displacement map. If the a color output is implicitly converted in the vector input, the first channel (red) value determines displacement along X axis. The second channel (green) the displacement along Y axis. If the input is a greyscale image, where both the channel values are equal, the input image will be displaced equally in both X and Y directions.

Scale X, Y

Separate scaling of the vector input in X and Y direction. Acting as multipliers by increasing or decreasing the strength of the displacement along their respective axes.

Outputs


Image

Standard image output.

Flip

This node flips an image at defined axis.

You can use this node to just flip or use it as a part of mirror setting. Mix half of the image to be mirrored with its flipped version to produce mirrored image.



Inputs

Image


Standard image input.

Properties

Axis

This can be either X or Y. Also, flipping can be done on both X and Y axis simultaneously.

Flip X, Flip Y, Flip X & Y



Outputs

Image

Standard image output.

Map UV


With the Map UV node objects can be “re-textured” after they have been rendered.

To apply a texture to individual enumerated objects the ID Mask Node could be used.

Inputs

Image

The new 2D texture.



UV

The input for UV render pass. See Cycles render passes.

Hint. To store the UV pass a multi-layer OpenEXR format could be used.

Properties

Alpha

Alpha threshold is used to fade out pixels on boundaries.

Outputs

Image

The resulting image is the input image texture distorted to match the UV coordinates. That image can then be overlay mixed with the original image to paint the texture on top of the original. Adjust alpha and the mix factor to control how much the new texture overlays the old.

Hint. When painting the new texture, it helps to have the UV maps for the original objects in the scene, it is recommended to keep those UV texture outlines around even, when shooting is done.

Lens Distortion

Use this node to simulate distortions that real camera lenses produce.

Inputs

Image

Standard image input.

Distortion

This creates a bulging or pinching effect from the center of the image.

Dispersion

This simulates chromatic aberrations, where different wavelengths of light refract slightly differently, creating a rainbow colored fringe.


Properties

Projector

Enable or disable slider projection mode. When on, distortion is only applied horizontally. Disables Jitter and Fit.

Jitter

Adds jitter to the distortion. Faster, but noisier.



Fit

Scales image so black areas are not visible. Only works for positive distortion.

Outputs


Image

Standard image output.

Movie Distortion

In the real world, all camera lenses produce some or the other sort of lens distortion. But, whatever we render has got no distortion. So, this node helps in removing distortion from movies or adding distortion to render to make our render blend in with the movie clip.

Usually, it is used while motion tracking.



Distortion vs Undistortion

Although, both, distortion of render and undistortion of movie clip are possible, and produce similar results, there is a difference between these two methods.

There are two kinds of lens distortion possible and, in simple terms, they can be said as:

When the movie clip is bulging out.

When the movie clip is bulging in.

For the first case, it is recommended to distort the render and leave the movie clip as it is, because, undistorting the movie clip will require extra pixel information, which is not available to Blender. Similarly, in the second case, it is recommended to undistort the movie clip and leave the render as it is, because, distorting the render will require those extra unavailable pixels. Doing the wrong method in the wrong case can create weird results around the edges, such as in the image shown.

Calculating Distortion

Before using this node, one has to calculate the lens distortion of the clip. This can be done by adjusting K1, K2 and K3 values in Movie Clip Editor > Properties ? Lens. For more information on how to edit those values, check this out.

Inputs

Image

Standard image input.

Properties


Movie Clip

Used to select the movie clip whose distortion is to be used. This can be useful if more than one movie clips are present, each having a different distortion setting. For controls see Data-Block Menu.

Distortion Method

Undistort

Used to undistort the image received, and is usually used for the raw distorted movie clip.



Distort

Used to distort the image received, and is usually used for rendered images.

Outputs

Image

Standard image output.
